



READ ME

SCHLAGE SECURITY MANAGEMENT SYSTEM EXPRESS V4.2.0

Please Note:

- This version DOES NOT support the obsolete E-BOLT product.
- This version DOES support specific versions of Windows Vista and Windows 7 (see below)

System Requirements for 4.2.0

Operating System: Compatible with: Microsoft Windows XP and XP Professional SP1/SP2, Windows Vista 32-bit (except Home or Starter Edition), Windows 7 32-bit & 64-bit Professional and higher

Hardware: Intel Pentium II processor (Pentium III or IV recommended), CD-Rom, Mouse or compatible pointing device, VGA or Super VGA monitor, Keyboard

Hard Disk Space: Hard Disk Space: 1 GB for software plus whatever is required for stored data

Memory: Memory: 256 MB RAM minimum or the memory required for the operating system, whichever is greater

Web Browser: To view generated reports IE 6 or higher (or a compatible browser) needs to be installed. If no browser is installed then the reports cannot be viewed.

64bit System Installation

On 64 bit systems an error message may occur at the end of installation. A Windows message may pop-up stating that the installation was incomplete. This message is an error and should be ignored, SMS Express has installed correctly.

Upgrade Instructions

It is possible to upgrade your system from a previous version of SMS Express. Follow the directions below to upgrade your system. (These instructions are also available in the Appendix of the User's Manual.)

Note: Program Settings and other individual settings will not be backed up and will need to be re-entered into the new version after upgrade.

1. **Backup the database**
 - a) The system is set, by default, to automatically backup the database whenever the system is closed. Make sure this feature is enabled. (See the Backup section of the Settings chapter for details.)
 - b) Close the system to backup the database.
2. **Copy the backed up database file to another location or folder**
 - a) Open the location of the backup file.
 - b) Copy the file.
 - c) Paste the copied file into a new directory of your choice.
3. **Uninstall the current version of the SMS express**

- a) Open the **Control Panel**.
- b) Open the **Add or Remove Programs** option.
- c) Select **Name** from the **Sort by** drop down box.
- d) Scroll down the list until you see **SMSExpress**. Select it.
- e) Click the **Remove** button. SMS Express will be uninstalled.
4. **Delete the Schlage Security Management System Express folder from Program Files** (Because of the ProXLator.exe program the folder will need to be manually removed).
 - a) Go to **My Computer**.
 - b) Click on **C:**
 - c) Click on **Program Files**.
 - d) Find and **Select the Schlage Security Management System Express** folder.
 - e) Right Click and select **Delete** from the drop down options. The Confirm Folder Delete window will open.
 - f) Click **OK**. The folder will be deleted.
5. **Install this version (4.2.0) of SMS Express** (See the **Installing/Starting SMS Express** chapter in the User's Manual for details)
6. **Restore the back up of the previous version**
 - a) Sign into SMS Express.
 - b) Go to **Facility>Restore Backup**.
 - c) Click **Yes**. The Select Facility to Restore window will open.
 - d) Navigate to the database that was backed up from the previous version and select the backup file.
 - e) Click **Open**. The Existing Facility File Found window will open.
 - f) Click **OK**.

The old Database has been attached to the new version of SMS Express and your upgrade is complete.

Technical Support

- Tel: 877-671-7011
- Email: Access_Control_TechProdSupport@irco.com